

Abaque des résistances de la série E12 montée en parallèle

	1	1.2	1.5	1.8	2.2	2.7	3.3	3.9	4.7	5.6	6.8	8.2	10	12	15	18	22	27	33	39	47	56	68	82
1	0,500	0,545	0,600	0,643	0,688	0,730	0,767	0,796	0,825	0,848	0,872	0,891	0,909	0,923	0,938	0,947	0,957	0,964	0,971	0,975	0,979	0,982	0,986	0,988
1.2		0,600	0,667	0,720	0,776	0,830	0,880	0,918	0,956	0,988	1,020	1,046	1,071	1,090	1,111	1,125	1,137	1,148	1,157	1,164	1,170	1,174	1,179	1,182
1.5			0,750	0,818	0,892	0,962	1,031	1,083	1,137	1,183	1,228	1,268	1,304	1,333	1,363	1,384	1,404	1,421	1,434	1,444	1,453	1,460	1,467	1,473
1.8				0,900	0,990	1,080	1,164	1,231	1,301	1,362	1,423	1,476	1,525	1,565	1,607	1,636	1,663	1,687	1,706	1,720	1,733	1,743	1,753	1,761
2.2					1,100	1,212	1,320	1,406	1,498	1,579	1,662	1,734	1,803	1,859	1,918	1,960	2,000	2,034	2,062	2,083	2,101	2,116	2,131	2,142
2.7						1,350	1,485	1,595	1,714	1,821	1,932	2,031	2,125	2,204	2,288	2,347	2,404	2,456	2,495	2,525	2,553	2,575	2,596	2,613
3.3							1,650	1,787	1,938	2,076	2,221	2,353	2,481	2,588	2,704	2,788	2,869	2,940	3,000	3,042	3,083	3,116	3,147	3,172
3.9								1,950	2,131	2,298	2,478	2,642	2,805	2,943	3,095	3,205	3,312	3,407	3,487	3,545	3,601	3,646	3,688	3,722
4.7									2,350	2,555	2,779	2,987	3,197	3,377	3,578	3,726	3,872	4,003	4,114	4,194	4,272	4,336	4,396	4,445
5.6										2,800	3,070	3,327	3,589	3,818	4,077	4,271	4,463	4,638	4,778	4,896	5,003	5,090	5,175	5,242
6.8											3,400	3,717	4,047	4,340	4,678	4,935	5,194	5,431	5,638	5,790	5,940	6,063	6,181	6,279
8.2												4,100	4,505	4,871	5,301	5,633	5,973	6,289	6,567	6,775	6,981	7,152	7,317	7,454